

P100 Wireless Player.

Simplicity, meet high fidelity. With the NuVo player portfolio, treating yourself to mastering-grade wireless audio is no longer a luxury too good to be true. Just get the party started with the P100 player.



NuVo's P100 player, a wireless single zone amplifier, offers 40 watts of power and also acts as its own source device, pulling together your favorite network-stored content, as well as accessing a wide variety of online music from great services like Rhapsody and Pandora®. Select your soundtrack easily, wirelessly, from NuVo's handheld controller or your favorite Apple or Android device, and then turn it up....because wireless home audio has never sounded so good.

- Enjoy your music anytime, anywhere, with quick access to music on your PC or Mac.
- Music from 100,000+ Internet Radio stations is right at your fingertips, streaming directly to your NuVo system.
- Mastering-grade, high-fidelity audio is delivered to every area of your home, and kept perfectly in sync.
- World-renown Audyssey™ music technology optimizes your listening experience with Dynamic Volume.
- The high-efficiency amplifier operates coolly and saves energy.

- Using the latest 802.11n wireless transmission, the system operates off the fastest signal and with the broadest coverage.
- Connect any storage device to the unit's USB port or audio line-in and play its content through your system.
- Connect your player to your existing home theater receiver or any other device to allow it to play your music through audio line-out.
- Every zone in your system can play and be controlled independently, so you can listen to your favorite album on the deck, while the kids listen to SiriusXM in the den.
- Wirelessly manage the entire system from the palm of your hand with your NuVo Controller or personal Apple or Android device.
- Start your system with one player, and when you want music in another room, simply add another.

P100 Wireless Player.

Specifications

Input/Output Connectors

Line Input	1 - TRS 3.5 mm stereo jack
Line Output	1 - TRS 3.5 mm stereo jack
Speaker Output	4 - Gold 5-way binding post
USB 2.0 Connection (Type A)	1
Local Area Network (LAN)	1 - RJ45

Supported Audio Formats

Music File (via USB or network)	MP3
	WMA
	AAC
	Ogg Vorbis
	FLAC
	WAV

Internet Radio:	Pandora®
	Sirius/XM
	Rhapsody
	TuneIn

IP Control

Apple iPod®
Apple iPhone®
Apple iPad®
Android Mobile
Android Tablet

Network Connectivity

LAN (Wired Connection)	10/100base-t Ethernet
Wireless Connection	MIMO, 2 TX + 2 RX Channels IEEE 802.11a/b/g/n

Amplifier Output

Rated Output Power (8 ohm)	40W (20W x 2)
Two channels driven 20 Hz – 20 KHz @ 0.5% distortion	
Rated Distortion (1/2 Power)	0.20%
Speaker Impedance	6 – 8 ohms
Frequency Response (20 - 20kHz)	+/-0.5 dB
Damping Factor	50+
Signal-to-Noise Ratio at rated output	94 dB A – weighted

Line Output:

Output Level	0-1000 mV RMS
Output Impedance	5 Ohms
Signal-to-Noise Ratio at rated output	88 dB A – weighted

Line Input:

Input Impedance	10 KOhms
Input Overload	2.3 V RMS

Audio Processing

Audyssey Dynamic Volume™	
Bass Equalization	+/-12 dB range
Treble Equalization	+/-12 dB range
Balance	

Regulatory Approvals

Safety	cTUVus, CE-LVD
EMC	FCC, IC, CE-EMC, C-Tick
Environmental Compliance	RoHS

Power Requirements

Input Voltage	100 – 240VAC, 50/60 Hz
Power Consumption (max)	70 W
Power Consumption (typical – 1/8 audio power)	13 W

Operating Temperature

0° C to 40° C

Physical Specifications

Unit Size (mm)	42 H x 187 W x 115 D
Unit Size (inch)	1.65 H x 7.36 W x 4.53 D
Unit Weight (kg)	0.613
Unit Weight (pounds)	1.35

Shipping Specifications

Unit Size (mm)	240 L x 230 W x 65.5 H
Unit Size (inch)	9.45 L x 9.06 W x 2.58 H
Unit Weight (kg)	1.30
Unit Weight (pounds)	2.87

NuVo reserves the right to change specifications without notice.

Office Toll Free: 866.796.4904

Office Direct: 859.817.7200

Email: sales@nuvotechnologies.com

Web: www.nuvotechnologies.com

P200 Wireless Player.

Never before have quality and simplicity blended in such perfect harmony as with NuVo's new P200 Wireless Player for the NuVo Wireless Audio System. High-fidelity, incredible variety, and true flexibility...now brought to you without wires.



Fill a room of your home with crisp, advanced high-fidelity audio, *wirelessly*, with the talented and versatile P200. Acting as both amplifier and source component, the P200 delivers 120 watts of power and streams content from networked computers, analog sources, Bluetooth enabled devices, as well as an abundance of internet-based services, guaranteeing both fantastic listening variety and truly superior sound.

- Enjoy your music anytime, anywhere, with quick access to music on your PC or Mac.
- Music from 100,000+ Internet Radio stations is right at your fingertips, streaming directly to your NuVo system.
- Mastering-grade, high-fidelity audio is delivered to every area of your home, and kept perfectly in sync.
- World-renown Audyssey™ music technology optimizes your listening experience with Dynamic Volume.
- The high-efficiency amplifier operates coolly and saves energy.

- Using the latest 802.11n wireless transmission, the system operates off the fastest signal and with the broadest coverage.
- Connect any storage device to the unit's USB port or audio line-in and play its content through your system.
- Connect any Bluetooth device, wirelessly, using the lossless aptX™ Bluetooth feature, streaming audio from your personal device directly to your NuVo system.
- Connect your player to your existing home theater receiver or any other device to allow it to play through audio line-out.
- Every zone in your system can play and be controlled independently, so you can listen to your favorite album on the deck, while the kids listen to SiriusXM in the den.
- Wirelessly manage the entire system from the palm of your hand with your NuVo Controller or personal Apple or Android device.
- Start your system with one player, and when you want music in another room, simply add another.

P200 Wireless Player.

Specifications

Input/Output Connectors

Line Input	1 - TRS 3.5 mm stereo jack
Line Output	1 - TRS 3.5 mm stereo jack
Setup Mic: (Audyssey)	1 - TS 3.5 mm stereo jack
Speaker Output	4 - Gold 5-way binding post
USB 2.0 Connection (Type A)	1
Local Area Network (LAN)	1 - RJ45

Supported Audio Formats

Music File (via USB or network)	MP3
	WMA
	AAC
	Ogg Vorbis
	FLAC
	WAV

Internet Radio:	Pandora®
	Sirius/XM
	Rhapsody
	TuneIn

IP Control

Apple iPod®
Apple iPhone®
Apple iPad®
Android Mobile
Android Tablet

Network Connectivity

LAN (Wired Connection)	10/100base-t Ethernet
Wireless Connection	MIMO, 2 TX + 2 RX Channels IEEE 802.11a/b/g/n

Amplifier Output

Rated Output Power (8 ohm)	120W (60W x 2)
Two channels driven 20 Hz – 20 KHz @ 0.5% distortion	
Rated Output Power (4 ohm)	120W (60W x 2)
Two channels driven 20 Hz – 20 KHz @ 0.5% distortion	
Rated Distortion (1/2 Power)	0.20%
Speaker Impedance	4 – 8 ohms
Frequency Response (20 - 20kHz)	+/-0.5 dB
Damping Factor	65+
Signal-to-Noise Ratio at rated output	92 dB A – weighted

Line Output:

Output Level	0-1000 mV RMS
Output Impedance	5 Ohms
Signal-to-Noise Ratio at rated output	88 dB A – weighted

Line Input:

Input Impedance	10 KOhms
Input Overload	2.3 V RMS

Audio Processing

Audyssey Dynamic Volume™	
Bass Equalization	+/-12 dB range
Treble Equalization	+/-12 dB range
Balance	

Regulatory Approvals

Safety	cTUVus, CE-LVD
EMC	FCC, IC, CE-EMC, C-Tick
Environmental Compliance	RoHS

Power Requirements

Input Voltage	100 – 240VAC, 50/60 Hz
Power Consumption (max)	150 W
Power Consumption (typical – 1/8 audio power)	31 W

Operating Temperature

0° C to 40° C

Physical Specifications

Unit Size (mm)	42 H x 229 W x 127 D
Unit Size (inch)	1.65 H x 9.02 W x 5.0 D
Unit Weight (kg)	1.11
Unit Weight (pounds)	2.45

Shipping Specifications

Unit Size (mm)	260 L x 240 W x 65.5 H
Unit Size (inch)	10.24 L x 9.45 W x 2.58 H
Unit Weight (kg)	2.0
Unit Weight (pounds)	4.41

NuVo reserves the right to change specifications without notice.

Office Toll Free: 866.796.4904

Office Direct: 859.817.7200

Email: sales@nuvotechnologies.com

Web: www.nuvotechnologies.com

P3100 Professional-Grade Player.

Offering three independent zones powered by one rack-mountable unit, all equipped with built-in digital source variety and supremely convenient wireless control, the P3100 is all about a truly custom home audio experience.



NuVo's P3100 professional series player features built-in access to both Internet Radio and your personal digital music collection, while delivering 40 watts of power and mastering-grade audio to three separate zones, all from the one central, hardwired location at the main equipment rack. Plus, the P3100 works in conjunction with the wireless P100 and P200 players, enabling users to enjoy the most customized solutions, perfect for any home.

- Enjoy your music anytime, anywhere, with quick access to music on your PC or Mac.
- Music 100,000+ Internet Radio stations is right at your fingertips, streaming directly to your NuVo system.
- Mastering-grade, high-fidelity audio is delivered to every area of your home, and kept perfectly in sync.
- World-renown Audyssey™ music technology optimizes your listening experience with Dynamic Volume.
- The high-efficiency amplifier operates coolly and saves energy.

- A single, rack-mountable unit provides three players, for three separate amplified zones.
- Hard wire multiple players with Ethernet for a clean, centralized installation.
- Connect any storage device to the unit's USB port or audio line-in and play its content through your system.
- Connect to your existing home theater receiver or any other device through audio line-out.
- Independent zone control for listening to your favorite album on the deck, while the kids listen to SiriusXM in the den.
- Wirelessly manage your music from the palm of your hand with your NuVo Controller or personal Apple or Android device.
- Start your system with one player, and when you want music in another room, simply add another.

P3100 Professional Series Player.

Specifications

Input/Output Connectors

Line Input	3 - TRS 3.5 mm stereo jack
Line Output	3 - TRS 3.5 mm stereo jack
Trigger Input	3 - TS 3.5 mm stereo jack
Trigger Output	3 - TS 3.5 mm stereo jack
Speaker Output	3 - (4 contact) pluggable
USB 2.0 Connection (Type A)	3
Local Area Network (LAN)	1 - Dual RJ45

Supported Audio Formats

Music File (via USB or network)	MP3
	WMA
	AAC
	Ogg Vorbis
	FLAC
	WAV

Internet Radio:	Pandora®
	Sirius/XM
	Rhapsody
	TuneIn

IP Control

Apple iPod®
Apple iPhone®
Apple iPad®
Android Mobile
Android Tablet

Network Connectivity

LAN (Wired Connection)	10/100base-t Ethernet
	Internal Ethernet switch to 3 independent zone nodes

Amplifier Output (typical of 3 zones)

Rated Output Power (8 ohm)	40W (20W x 2)
	Two channels driven 20 Hz – 20 KHz @ 0.5% distortion
Rated Distortion (1/2 Power)	0.20%
Speaker Impedance	6 – 8 ohms
Frequency Response (20 - 20kHz)	+/-0.5 dB
Damping Factor	50+
Signal-to-Noise Ratio at rated output	92 dB A – weighted

Line Output:

Output Level	0-1000 mV RMS
Output Impedance	5 Ohms
Signal-to-Noise Ratio at rated output	91 dB A – weighted

Line Input:

Input Impedance	10 KOhms
Input Overload	2.3 V RMS

Audio Processing

Audyssey Dynamic Volume™	
Bass Equalization	+/-12 dB range
Treble Equalization	+/-12 dB range
Balance	

Regulatory Approvals

Safety	cTUVus, CE-LVD
EMC	FCC, IC, CE-EMC, C-Tick
Environmental Compliance	RoHS

Power Requirements

Input Voltage	100 – 240VAC, 50/60 Hz
Power Consumption (max)	200 W
	(typical – 3 zones, 1/8 audio power) 42 W

Operating Temperature

0° C to 40° C

Physical Specifications

Unit Size (mm)	44 H x 430 W x 250 D
Unit Size (inch)	1.73 H x 16.93 W x 9.84 D
Unit Weight (kg)	2.81
Unit Weight (pounds)	6.20

Shipping Specifications

Unit Size (mm)	565 L x 328 W x 130 H
Unit Size (inch)	22.24 L x 12.91 W x 5.12 H
Unit Weight (kg)	3.50
Unit Weight (pounds)	7.72

NuVo reserves the right to change specifications without notice.

Office Toll Free: 866.796.4904

Office Direct: 859.817.7200

Email: sales@nuvotechnologies.com

Web: www.nuvotechnologies.com